The versatile Power-Buddies UPSes are simple to install and allows you to power various devices during power outages. With multiple-voltage DC outputs, you can power various DC devices with different voltage requirements.

Keep the internet up so you can continue to work from home during power outages by connecting your Router and ONU (Optical Network Unit) to the UPS. The USB Ports provided on the 165Wh unit also allows you to charge your mobile devices such as cell phones and tablets.

For the advanced users, connect your VoIP (Voice over IP) phone and an AP (Access Point) via the Gigabit Power Over Ethernet (POE) ports.

For those with security requirements, you can connect CCTV cameras, DVRs, NVRs and even POE switches during power interruptions for peace of mind.

Model	 **60W / 165Wh**	 **100W / 165Wh**	 **100W / 75Wh**
Input	**100 ~ 240Vac 50/60Hz** **12 ~ 24V DC/Solar (2.5A)**		**100 ~ 240Vac 50/60Hz**
Output	**1 × 9V/12V (2A)** **3 × 12V(8A)** **1 × 48V(2A)** **2 × 24V/48V (POE 1 Gig)** **1 × 5VDC +2 × USB(2.4A)**		**1 × 9V/12V (3A)** **5 x 12V(3A)** **1 x 48V(2A)** **1 × 15V/24V (POE 1 Gig)**
Output polarity	**DC - Output** ⊖—⊂—⊕ **/ Passive POE (+ pins 4,5 - pins 7,8)**		
Max Power output	**60W**	**100W**	**100W**
Battery capacity	**52000mah**		**24000mah**
Charge time	**+- 2 Hours**	**+- 2 Hours**	**+- 5 to 6 Hours**
Battery Specification	**LifePO4**		
Dimension (mm)	**214 × 158.5 x 86**	**214 × 158.5 x 86**	**258 x 229 x 52**

www.tech-buddies.co.za